



HX 3000 TB UK

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- · Entire group guaranteed 3 years
- **HONDA** Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.















This product meets the Qualigen charter, which aims to ensure a high level of quality and guarantee the safety of users. Qualigen: commitment to safety and quality.

HX 3000 TB UK

GENERAL SPECIFICATIONS

Range	INTENS		
Frequency (Hz)	50 Hz		
Max power (kW) *	3		
Nominal voltage (V)	230		
Number of Phase	Single phase		
Fuel	Petrol		
Tank (L)	3.10		
75% cons. (I/h) *	1.30		
75% Autonomy (h) *	2.40		
Sound power level guaranteed LwA dB(A)	95		
Acoustic pressure level @1m in dB(A)	81		
Acoustic pressure level @7m in dB(A)	67		

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX200
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	196
Oil system capacity including filters (L)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	Н

PLUGS AND PANEL DESCRIPTIVE

2 115V 16A sockets - circuit breaker + 1 socket 230V 16A - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661





HX 3000 TB UK

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS

	R06	Trolley kit for 2 and 3 kW generating sets.
NOVA A NOVA A No	R18	Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000)
	R50	16A blue 230V male plug - Sold per 1 or 10
	R51	16A yellow 115V male plug - Sold per 1 or 10
Co	R54	Adaptator R54 16A/13A adaptator unit. Sold per 1 or 3
	R55	ADAPTATOR R55 16A/13A adaptator economy. Sold per 1 or 3
	R56	ADAPTATOR R56 16A/13A double adaptator. Sold per 1 or 3
Countries Canada del Canada del C	RBH1	Box of 24 o.5L cans of oil or 20 1 L cans of oil (SAE 15W40)
Control of the Contro	RBH0-5	Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).
sk-pants film	RHO	Cover for SDMO 's generating sets, welding sets and water pumps



